

| Channel     | Position | U# | Inst Type & Access & Load | Purpose    | Clr & Gbo | Dim | Addr |
|-------------|----------|----|---------------------------|------------|-----------|-----|------|
| <b>(1)</b>  | PIPE 4   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 17  | 1/17 |
| <b>(2)</b>  | PIPE 4   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 18  | 1/18 |
| <b>(3)</b>  | PIPE 4   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 19  | 1/19 |
| <b>(4)</b>  | PIPE H   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 12  | 1/12 |
| <b>(5)</b>  | PIPE 4   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 16  | 1/16 |
| <b>(6)</b>  | PIPE 6   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 29  | 1/29 |
| <b>(7)</b>  | PIPE 6   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 30  | 1/30 |
| <b>(8)</b>  | PIPE 6   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 34  | 1/34 |
| <b>(9)</b>  | PIPE H   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 33  | 1/33 |
| <b>(10)</b> | PIPE 6   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 37  | 1/37 |
| <b>(11)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 25  | 1/25 |
| <b>(12)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 26  | 1/26 |
| <b>(13)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 52  | 1/52 |
| <b>(14)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 51  | 1/51 |
| <b>(15)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 42  | 1/42 |
| <b>(16)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 63  | 1/63 |
| <b>(17)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 60  | 1/60 |
| <b>(18)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 67  | 1/67 |
| <b>(19)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 73  | 1/73 |
| <b>(20)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Frontlight | -, T:-    | 68  | 1/68 |
| <b>(21)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Hi Side >  | -, T:-    | 23  | 1/23 |
| <b>(22)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Hi Side >  | -, T:-    | 24  | 1/24 |
| <b>(23)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Hi Side >  | -, T:-    | 27  | 1/27 |
| <b>(24)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Hi Side >  | -, T:-    | 62  | 1/62 |
| <b>(25)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Hi Side >  | -, T:-    | 61  | 1/61 |

| Channel     | Position | U# | Inst Type & Access & Load | Purpose   | Clr & Gbo | Dim | Addr  |
|-------------|----------|----|---------------------------|-----------|-----------|-----|-------|
| <b>(26)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 65  | 1/65  |
| <b>(27)</b> | PIPE 12  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 98  | 1/98  |
| <b>(28)</b> | PIPE 12  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 97  | 1/97  |
| <b>(29)</b> | PIPE 12  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 108 | 1/108 |
| <b>(30)</b> | PIPE 14  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 127 | 1/127 |
| <b>(31)</b> | PIPE 14  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 126 | 1/126 |
| <b>(32)</b> | PIPE 14  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 129 | 1/129 |
| <b>(33)</b> | PIPE 16  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 148 | 1/148 |
| <b>(34)</b> | PIPE 16  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 147 | 1/147 |
| <b>(35)</b> | PIPE 16  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 149 | 1/149 |
| <b>(41)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 49  | 1/49  |
| <b>(42)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 41  | 1/41  |
| <b>(43)</b> | PIPE 8   |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 70  | 1/70  |
| <b>(44)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 74  | 1/74  |
| <b>(45)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 69  | 1/69  |
| <b>(46)</b> | PIPE 10  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 71  | 1/71  |
| <b>(47)</b> | PIPE 12  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 103 | 1/103 |
| <b>(48)</b> | PIPE 12  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 111 | 1/111 |
| <b>(49)</b> | PIPE 12  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 113 | 1/113 |
| <b>(50)</b> | PIPE 14  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 133 | 1/133 |
| <b>(51)</b> | PIPE 14  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 135 | 1/135 |
| <b>(52)</b> | PIPE 14  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 134 | 1/134 |
| <b>(53)</b> | PIPE 16  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 152 | 1/152 |
| <b>(54)</b> | PIPE 16  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 155 | 1/155 |
| <b>(55)</b> | PIPE 16  |    | Source 4 36∞ 750w         | Hi Side > | -, T:-    | 156 | 1/156 |

| Channel     | Position | U# | Inst Type & Access & Load   | Purpose       | Clr & Gbo | Dim | Addr  |
|-------------|----------|----|-----------------------------|---------------|-----------|-----|-------|
| <b>(61)</b> | PIPE E   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 53  | 1/53  |
|             | PIPE 8   |    | "                           | "             | "         | "   | "     |
| <b>(62)</b> | PIPE I   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 50  | 1/50  |
|             | PIPE G   |    | "                           | "             | "         | "   | "     |
| <b>(63)</b> | PIPE E   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 64  | 1/64  |
|             | PIPE C   |    | "                           | "             | "         | "   | "     |
| <b>(64)</b> | PIPE I   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 66  | 1/66  |
|             | PIPE G   |    | "                           | "             | "         | "   | "     |
| <b>(65)</b> | PIPE E   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 105 | 1/105 |
|             | PIPE C   |    | "                           | "             | "         | "   | "     |
| <b>(66)</b> | PIPE I   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 100 | 1/100 |
|             | PIPE G   |    | "                           | "             | "         | "   | "     |
| <b>(67)</b> | PIPE E   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 142 | 1/142 |
|             | PIPE C   |    | "                           | "             | "         | "   | "     |
| <b>(68)</b> | PIPE I   |    | Selecon Rama 7" Fresnel 1kW | Toplight      | -, T:-    | 146 | 1/146 |
|             | PIPE G   |    | "                           | "             | "         | "   | "     |
| <b>(71)</b> | PIPE C   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 303 | 1/303 |
| <b>(72)</b> | PIPE E   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 318 | 1/318 |
| <b>(73)</b> | PIPE G   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 333 | 1/333 |
| <b>(74)</b> | PIPE I   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 348 | 1/348 |
| <b>(75)</b> | PIPE C   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 363 | 1/363 |
| <b>(76)</b> | PIPE E   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 378 | 1/378 |
| <b>(77)</b> | PIPE G   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 393 | 1/393 |
| <b>(78)</b> | PIPE I   |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 408 | 1/408 |
| <b>(79)</b> | PIPE 16  |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 423 | 1/423 |
| <b>(80)</b> | PIPE 16  |    | ETC Selador Desire D60      | LED Backlight | -, T:-    | 438 | 1/438 |

| Channel      | Position | U# | Inst Type & Access & Load          | Purpose                        | Clr & Gbo | Dim | Addr  |
|--------------|----------|----|------------------------------------|--------------------------------|-----------|-----|-------|
| <b>(81)</b>  | PIPE 16  |    | ETC Selador Desire D60             | LED Backlight                  | -, T:-    | 453 | 1/453 |
| <b>(82)</b>  | PIPE 16  |    | ETC Selador Desire D60             | LED Backlight                  | -, T:-    | 468 | 1/468 |
| <b>(91)</b>  | PIPE 5   |    | Source 4 36∞ 750w                  | Front Moving<br>Special        | -, T:-    | 31  | 1/31  |
|              | "        |    | Apollo Right Arm                   | Moving Arm --<br>Front Special | "         | 288 | 1/288 |
|              | "        |    | DMX Iris                           | DMX Iris --<br>Front Special   | "         | 292 | 1/292 |
| <b>(92)</b>  | PIPE 5   |    | Source 4 36∞ 750w                  | Front Moving<br>Special        | -, T:-    | 35  | 1/35  |
|              | "        |    | Apollo Right Arm                   | Moving Arm --<br>Front Special | "         | 293 | 1/293 |
|              | "        |    | DMX Iris                           | DMX Iris --<br>Front Special   | "         | 297 | 1/297 |
| <b>(101)</b> | PIPE 5   |    | Selecon Rama 7" HL Fresnel<br>750w | Houselights                    | -, T:-    | 28  | 1/28  |
|              | "        |    | "                                  | "                              | "         | "   | "     |
|              | "        |    | "                                  | "                              | "         | "   | "     |
| <b>(102)</b> | PIPE 3   |    | Selecon Rama 7" HL Fresnel<br>750w | Houselights                    | -, T:-    | 4   | 1/4   |
|              | "        |    | "                                  | "                              | "         | "   | "     |
|              | "        |    | "                                  | "                              | "         | "   | "     |
| <b>(103)</b> | PIPE H   |    | Desisti Fresnel 500w               | Aisle Light                    | -, T:-    | 13  | 1/13  |
|              | PIPE K   |    | "                                  | "                              | "         | "   | "     |
|              | PIPE A   |    | "                                  | "                              | "         | 3   | 1/3   |
|              | PIPE 1   |    | "                                  | "                              | "         | "   | "     |